## 1000 AND PAS 250 1000 PODIUM UNIT ASSEMBLY GUIDE

- 1 X FOLDING FRAME
- 1 X PLATFORM
- 1 X LADDER
- 2 X STABILISER(FOR PAS 250 COMPLIANCE
- 2) OPEN FRAME AND LOCK MECHANISM
- 3) FIT PLATFORM AT CORRECT HEIGHT
- 4) CLIP UPPER BRACE OF LADDER ABOVE RINGS ON VERTICALS WITH ASSEMBLED HOOKS AT TOP
- 5) POSITION UNIT AND LOCK CASTORS
- 6) FIT STABILISERS TO BACK VERTICALS (FOR PAS 250 COMPLIANCE)
- 7) USE LADDER TO ACCESS PLATFORM
- 8) CLOSE AND LOCK GATE



**Dimensions** 

Platform at 1M x Width - 0.65M x

Depth 1.3M

Working Height — 3M (Max)

**Dimensions** 

Folded Height – 2.05M x Width -

0.25M x Depth - 1.3M

Weight — 31Kg Safe Working Load -150kg

PAS 250 — 35Kg(Mini Stabilisers))

Manufactured under an ISO9001:2008 **Quality System** 

Complies fully with the Working at Height Regulations 2005 and PAS250 **Specifications** 

Lightweight all Aluminium Construction

For further information or assistance, please contact Safety Platforms Limited Tel 01924 420820 or visit: www.safetyplatforms.co.uk


## **IMPORTANT SAFETY NOTES**




ALWAYS READ THE INSTRUCTIONS BEFORE USING PODIUM



NEVER USE A PODIUM WITH DAMAGED OR MISSING COMPONENTS




NEVER OVERREACH




NEVER HAVE MORE THAN ONE PERSON ON THE PLATFORM



NEVER USE ON UNEVEN OR SLOPING SURFACES




DO NOT MOVE PODIUM IF A PERSON IS STILL ON IT



NEVER USE BOXES FOR EXTRA HEIGHT, STAND ONLY ON THE PLATFORM



NEVER USE PODIUMS AS A MEANS OF ACCESS TO ANOTHER PLACE



**ELECTRICAL POWER LINES** 

ALWAYS LOCK ALL CASTORS WHEN PODIUM IS SITED, AND BEFORE USE.

## BE AWARE OF THE FOLLOWING:

- A. DO NOT USE ON LOOSE OR SLIPPERY SURFACES.
- B. NEVER STAND ON THE ACCESS LADDER TO WORK
- C. WORKING PLATFORM MUST BE LEVEL
- D. INSPECT BEFORE USE.
- E FACE THE FOLDING BACK SECTION WHEN ASCENDING
- G. ENSURE THE GATE IS CLOSED AND LOCKED BEFORE USE
- H. BEWARE OF FINGER TRAPS.
- J. TO MOVE UNIT UNLOCK GATE AND DISMOUNT, UNLOCK CASTORS AND RE-LOCATE.
- K. IF IN DOUBT DO NOT GUESS CONSULT YOUR SUPPLIER.
- L. SEE OVERLEAF FOR COMPONENT CHECKLIST